How-To: Universal AP van WiNG OS 7 omzetten naar HiveOS via CLI

Console aansluiten	Putty starten	Com # Speed 115200	
Inloggen	Username: admin Password: admin123		
Enter stand alone mode	AP adoption discovery process in progress...To cancel and boot in Standalone mode, type (s):	S	
Enter console mode	Please press Enter to activate this console.	"Enter"	
Inloggen	Username: admin Password: admin123	Nieuw password ingeven en bevestigen	Password: test Password: test
Controleer firmware versie	Show version	Version 7.5.0.0-005R (of hoger)	
Enable config mode	Enable	> word #	
Herstart in recovery mode	Operational-mode xiq-cloud force	AP reboot automatisch	
Inloggen	Username: admin Password: admin123	BusyBox v1.17.4 built-in shell (ash) Enter 'help' for a list of built-in commands.	
Enter Service Personnel CLI	AP adoption discovery process in progress...To cancel and boot in Standalone mode, type (s):	PPP	
Reset boot mode naar HiveOS	cset factoryDefault hiveos	AP reboot automatisch in HiveOS	
Console aansluiten	Putty starten	Com # Speed 9600	
Inloggen	Username: admin Password: aerohive		
Controleer firmware versie	Show version	Version: HiveOS 10.2r4 build-252751 (of hoger)	

Vragen of advies nodig? Neem contact op met onze experts!
Telefoon: +31 (0)70 764 06 00
E-mail: Support@kappadata.nl

Kappa Data
Laan van Zuid Hoorn 51
2289 DC Rijswijk